

COSY™

6 DIGIT JUMBO LED CLOCK

6" High LED Digits

Model : CS606UD

99 Hours / 99 Minutes Programmable Up / Down Count Stopwatch



Features :

- ★ Jumbo 6" High bright RED LED digits > visible from more than 100 feet distance.
- ★ Normal Clock function with daily alarm .Selectable 12 or 24 Hour Display Format.
- ★ 99 Hours / 99 minutes programmable Stopwatch can be set to start counting up or down from any preset time.
- ★ Internal Battery backup maintains time during a power failure ,the clock will start to display accurate time as soon as the power is restored.(back up is for normal clock function only). In case of power failure stopwatch function will be reset .
- ★ Wired remote control with simple push buttons & switches to set time and control stopwatch.

CLOCK TIME SETTING :

Select the clock in 24 Hour mode .Select to CLOCK mode.

Simultaneously Keep pressed TIME button and any button H+ , M+ to change the time .

ALARM SETTING :

Select the clock in 24 Hour mode .Select to CLOCK mode.

Simultaneously Keep pressed ALARM button and any button H+ , M+ to set the Alarm time .

STOP WATCH MODE :

Select STOPWATCH mode : Select UP or DOWN COUNT mode.

Select stopwatch run time mode : 99 Hours or 99 minutes

In 99 Hour mode it will display HH:MM:SS(Hours:Minutes: Seconds)

In 99 Minutes mode it will display MM:SS:SS (Min:Sec:100ths of Sec)

SET THE START TIME : Simultaneously keep pressed TIME button and H+ , M+ , S+ to set the start time.

To set the start time to 00:00:00 : Simultaneously Keep pressed TIME button along with RESET button

Use START/STOP button to start or pause the stopwatch .

RESET button will make the clock show set START time.

CAUTION: While using with remote control keep the main clock controls towards :
24 Hours , 99 Minutes , UP & CLOCK position.

Specifications :

Dimensions & weight : 36 inches x 9 inches x 1.5 inches x 3 kgs appx.

Enclosure : Aluminum frame with black powder coating.

Power : 12 volt DC supply.

Power consumption : 10 Watts appx.

Battery use : Use 12V 7.5AH or better rating external battery at DC socket.

100V -220V AC use : Use power adapter of 12VDC 2A or better rating .

Applications : Indoor or outdoor use recommended with protection from direct rains.

Recommended for : Sports and Fitness Centers ,Large Offices, Hotels & Restaurants, Schools ,Factories, Ships etc .

Manufactured by:

COSY COMMUNICATIONS , 1, Indraprastha Enclave , Sewla, Majra, Dehradun - 248 171 (INDIA)

Tele:91-135-2640816 E-Mail: cosycom@gmail.com , Web : www.cosycom.com



Optional Item:
Wired remote control.