

COSY™

Model : CT3D6

Old ref # : KTD3DU6

3 DIGIT TOKEN NUMBER DISPLAY

With Single Key Automatic Number Increment Facility.

UP /DOWN COUNTER



6 Inches High Bright LED Characters



Sturdy Compact Plastic Molded Control Unit.
Low cost 3 core interconnecting cables

Product Information & Operating Instructions

Applications:

COSY Token Display System are ideal for Serving Counters in Offices, Banks, Airports, Doctors-Clinics, Restaurants , Canteens and other such places where people have to wait in line for their turn. These systems allow customers to wait without having to stand in line, once their number is displayed then only they have to come to the counter for their turn.

Sounds bell with calling number. Option to automatically show incremented or decremented token numbers by pressing a single key.

Features :

- * Simple operation and easy to install.
- * Large sized 6 inches high RED LED Displays, visible from more than 100 feet distance.
- * Single key automatic UP /DOWN counting , sounds bell with every change of number.
- * Additional Two pin modular socket provided to increase numbers through external pulses from any remote push button , contact switch etc. (Caution : Do not give any electrical pulses)
- * Feather touch heavy duty key board.
- * Robust design. Lightweight ABS Plastic molded control cabinets & lightweight LED displays.
- * Solid state high efficiency circuit with 8 bit micro controller.

Installation :

1. Connect the Display with main control unit by connector cable provided.
2. Connect Mains cable of console to 100 to 240 VAC . (Also connect 12 Volt Battery or UPS for back-up if required). Switch ON the system by RED Power ON/OFF switch provided at side.
3. Select the required new number flashing duration by keeping pressed a number key + B Key before switching ON the system. e.g. (1 + B makes display flash for 1 sec.) (5 + B for 5 sec.)
4. If desired Bell can be switched off by selecting the switch at display.

Operation:

Manual Mode : Press any required number of up to 3 digits while watching in small display of console. Use Clear Key **(C)** if required. Press the Bell Key **(B)** to send the number in main LED display and sound the bell . To call the same number again just press **(B)** Key.

Auto Mode : Press any required starting number up to 3 digits in Manual mode.

Change the switch to Auto Mode . Now when any of the number key 0 to 9 is pressed , the display will show the incremented next token number . (Automatic bell also sounds with every change of number).

Use Clear Key **(C)** to decrease the numbers serially in auto mode .

Caution :

Do not install or remove the cable of display while the system power is ON.

Specifications:

Power Supply : 12VDC 7Ah or better rating battery or 100 - 240Volts AC

Dimensions & Weight : Display Units: 18 inches X 11 inches X 1.25 inches X 1200 gms appx.
Control Unit: 7 inches X 6.5inches X 2.5 inches x 600 gms appx.

Connecting cable : 3 core cable with 9 pin D connectors. Standard cable length provided is 10 meters. Maximum recommended cable length 25 meters.

Accessories Included :

External wired remote control having 2 push buttons with 3 meter Cable to serially increase or decrease the numbers in Auto Mode. (Mechanical contact only >> like a bell switch)

Manufactured by:

COSY COMMUNICATIONS , 1, Indraprastha, Sewla, Majra, Dehradun - 248 171 , INDIA

Tele: 91-135 -2640816 E-Mail : cosycom@gmail.com , Web : www.cosycommunications.com