

3 DIGIT - FOUR NUMBER TOKEN DISPLAY



COSY Token Display System are ideal for Serving Counters in Offices, Banks, Airports, Doctors- Clinics, Restaurants and other such places where people have to wait in line for their turn. These systems allow customers to wait without having to stand in line, once their number is displayed then only they have to come to the counter for their turn.

Sounds musical chime with every new called number.


Features :

- ★ Simple operation and easy to install.
- ★ Large sized 4 inches high RED LED Displays, visible from 100 feet distance.
- ★ Pleasant musical bell sound on every change of number and the display flashes.
- ★ Feather touch heavy duty key board.
- ★ Robust design. Lightweight ABS Plastic moulded control cabinets & lightweight LED displays.
- ★ Solid state high efficiency circuit with 8 bit micro controller.

Installation :

1. Connect the Display with main control unit by connector cable provided. Screw the connectors firmly.
2. Connect Power adapter to either DC socket of main control unit or at Display as suitable
Switch ON the system by Power ON/OFF switch of control unit.
3. If desired Bell can be kept switched off by selecting the switch provided at display.

Operation:

Keep pressed display 1 key and from other hand enter any 3 digit number by keypad. .
As soon as you release the display 1 key the control unit will send data to first display of main board.
Similarly send numbers to other three displays of main board by using display 2 and display 3 keys.
To change the number repeat above steps for required display .
If any of the display has to be cleared to zero then use clear key  along with display key.

To reset all number to 0 keep pressed the C key long for more than 2 seconds .
To call any number again just press the display key of that number .

CAUTION :

Do not install or remove the cable of display while the system power is ON.

Specifications:

Power Supply : Use a 12VDC 3 Amp or better rating power supply , If required use with UPS for power backup.

Dimensions & Weight : Display Unit : 30 inches X 12 inches X 1 inches x 3 kg appx
Control Unit: 7 inches X 6.5 inches X 2.5 inches x 700 gms appx.

Connecting cable : 3 core cable with 9 pin D connectors. Standard cable length provided is 10 meters.
Maximum recommended cable length 25 meters.

Manufactured by:

COSY COMMUNICATIONS , 1, Indraprastha, Sewla, Majra, Dehradun - 248 171 , INDIA

Tele: 91-9358106627 E-Mail: cosycom@gmail.com , Web : www.cosycommunications.com