

COSY™

6 DIGIT JUMBO LED CLOCK

10" High LED Digits

Model : CS610UD

99 Minutes / 99 Hours Programmable Up / Down Count Stopwatch



Features:

- ★ Jumbo 10" High bright RED LED digits > visible from more than 200 feet distance. (Double sided clocks also made against order)
- ★ Normal Clock function with daily alarm .Selectable 12 or 24 Hour Display Format.
- ★ 99 Minutes or 99 Hours programmable Stopwatch can be set to start counting up or down from any preset time.
- ★ Internal Battery backup maintains time during a power failure ,the clock will start to display accurate time as soon as the power is restored.(back up is for normal clock function only). In case of power failure stopwatch function will be reset .
- ★ Simple push buttons & switches to set time and control Stop watch.

CLOCK MODE

TIME SETTING :

Select the clock in 24 Hour mode .Select to **CLOCK** mode.
Simultaneously Keep pressed **TIME** button and any button
H+ , H- , M+ , M- to change the time .

ALARM SETTING :

Select the clock in 24 Hour mode .Select to **CLOCK** mode.
Simultaneously Keep pressed **ALARM** button and any button
H+ , H- , M+ , M- to set the Alarm time .

STOP WATCH MODE :

Select **STOPWATCH** mode. Select **UP** or **DOWN** COUNT mode.

SET THE START TIME : Select 99 Minute or 99 Hour stopwatch mode.

Simultaneously keep pressed **TIME** button and H+ , M+ , S+ buttons to set the Stopwatch start time.

TO SET THE START TIME to 00:00:00 : Simultaneously Keep pressed **TIME** button along with **RESET** button .

CAUTION: To use this clock with remote control keep mode buttons in main clock controls towards 24 HOUR , CLOCK , 99 MINUTE & UP position .

Specifications :

Dimensions & weight : 55 inches x 12 inches x 1.5 inches x 5 kgs appx.

Double side clock also have same dimensions but weigh 7.5 kg appx.

Enclosure : Aluminum frame with black powder coating.

Power : 12 volt DC supply.

Power consumption : Single sided clock : 25 Watts appx.

Double sided clock : 40 Watts appx.

Battery use : 12V 7.5AH or better rating battery can be connected at DC socket.

100V -220V AC use : Use power adapter of 12VDC 5A rating .

Applications : Indoor or outdoor use recommended with protection from direct rains.

Recommended for : Sports and Fitness Centers ,Large Offices, Hotels & Restaurants, Schools ,Factories, Ships etc .

Manufactured by:

COSY COMMUNICATIONS , 1, Indraprastha Enclave , Sewla, Majra, Dehradun - 248 171 (INDIA)

Tele:91-135-2640816 E-Mail: cosycom@gmail.com , Web : www.cosycom.com



Control panel.



Optional Item:
Wired remote control.