

COSY™

Model : CT5D10

5 DIGIT TOKEN NUMBER DISPLAY

With Single Key Automatic Number Increment Facility.
UP /DOWN COUNTER



Jumbo 10 Inches High Bright LED Digits



Sturdy Compact Plastic Molded Control Unit.

Slim 3 core interconnecting cables with modular connectors

Product Information & Operating Instructions

Applications:

COSY Token Display System are ideal for Serving Counters in Offices, Banks, Airports, Doctors-Clinics, Restaurants , Canteens and other such places where people have to wait in line for their turn. These systems allow customers to wait without having to stand in line, once their number is displayed then only they have to come to the counter for their turn.

Sounds beep with change of calling number. Option to automatically increase or decrease token numbers serially by pressing a single key.

Features :

- * Simple operation and easy to install.
- * Jumbo 10 inches high RED LED Displays, visible from more than 200 feet distance.
- * Single key automatic UP /DOWN counting & pleasant bell with every change of number.
- * Feather touch heavy duty key board.
- * Robust design. Lightweight ABS Plastic molded control cabinets & lightweight LED displays.
- * Solid state high efficiency circuit with 8 bit micro controller.

Installation :

1. Connect the Display with main control unit by connector cable provided.
2. Connect Mains cable of console to 100 to 240 VAC . (Also connect 12 Volt Battery at DC socket or UPS for back-up if required). Switch ON the system by RED Power ON/OFF switch provided at side.
3. Select the required new number flashing duration by keeping pressed a number key + B Key before switching ON the system. e.g. (1 + B makes display flash for 1 sec.) (5 + B for 5 sec.)
4. If desired Bell can be switched off by selecting the switch provided at display.

Operation:

Manual Mode : Press any required number of up to 5 digits while watching in small display of console. Use Clear Key **(C)** if required. Press the Bell Key **(B)** to send the number in main LED display and sound the beep . To call the same number again just press **(B)** Key.

Auto Mode : Press any required starting number up to 5 digits in Manual mode.

Change the switch to Auto Mode . Now when any of the number key 0 to 9 is pressed , the display will show the incremented next token number . (Automatic bell also sounds with every change of number).

Clear Key **(C)** will decrease the number by one in auto mode .

To call the same number again just press **(B)** Key.

Caution :

Do not install or remove the cable of display while the system power is ON.

Specifications:

Power Supply : 12V DC , 100 - 240Volts AC Power adapter is shipped with system

Dimensions : Display Unit : 43 Inches x 14 inches x 1.5 inches x 5 Kgs appx.

Control Unit : 7 inches X 6.5inches X 2.5 inches x 600 gms appx.

Connecting cable : 3 core cable with Modular connector at display and 9 pin D connector at Control unit.

Standard cable length shipped is 10 meters. Maximum recommended cable length 25 meters.

Accessories Included :

Two button external wired remote control with 3 meter Cable to increase or decrease the numbers in Auto Mode.

Manufactured by:

COSY COMMUNICATIONS , 1, Indraprastha, Sewla, Majra, Dehradun - 248 171 , INDIA

Tele: 91-135 -2640816 E-Mail : cosycom@gmail.com , Web : www.cosycom.com