

COSY™


6 DIGIT LED STOPWATCH

with 99 Hours / 99 Minutes Count Up Stopwatch Function

Model: CS604LUD-F



New Model With Display Freeze Function.



Wired remote control having 3 buttons for START ,STOP & RESET

Features :

- ★ Attractive Big Size High bright RED LED Characters >>suitable for daylight use.
- ★ Selectable 12 or 24 Hour Display Format.
- ★ Daily alarm . Alarm automatically stops after sounding for 15 seconds.
- ★ Count Up / Countdown Stop Watch function . Two stopwatch run times are selectable .
In first mode it can up-count upto 99 minutes with an accuracy of 1/100th of second (MM:SS:SS display).
In other mode Stop watch has 99 hour stop watch function .(HH:MM:SS display).
- ★ Separate START ,STOP & RESET buttons to control Stop watch functions .
- ★ Display Freeze option while stopwatch continues to run in background.
- ★ External wired remote control also provided for controlling the Stopwatch from distance , .
- ★ Internal Battery backup maintains daily time during a power failure ,the clock will start to display accurate time as soon as the power is restored. (back up is for normal daily clock time only , in stopwatch mode it will reset)
- ★ Sturdy Black powder coated Aluminum frame .

Operating Instructions :

TIME SETTING :

Simultaneously Keep pressed TIME button and any button H+, H- , M+, M-

ALARM SETTING :

Simultaneously keep pressed ALARM button and any button H+, H- , M+, M- to set the alarm time.

STOP WATCH MODE :

Select UP or DOWN count mode .

Select 99 MINUTES or 99 HOURS stopwatch run time.

Set the required stopwatch start time by simultaneously pressing TIME button with H+, M+, S + buttons.

To reset the countdown start time to 00:00:00 press the RESET button for 2 seconds.

Use START, STOP & RESET buttons to control stopwatch functions.

If START button is pressed during running stopwatch then it will freeze the display till this button is kept pressed.

At finish of countdown it will sound a beep .

Note : stopwatch will keep the countdown start time in memory to allow for repeated starts from same time.

Specifications

Clock Accuracy : 2 minutes per month or better . Lithium battery installed inside for RTC time backup.

POWER : Operate with 12V DC power supply . External Power adapter for use with 100-240V AC is included.

All clocks shipped to customers in USA & CANADA are fixed with matching power cords for 110V power outlets.
Table and wall mounting provision.

Dimensions & Weight : Size of clock is appx. 26 inches x 6.5 inches x 1.5 inches and weighs appx 2 Kgs.

Recommended for : Sports and fitness Centers, Large Homes , Offices, Shops, Hotels & Restaurants, Automobiles , Ships etc . High brightness LEDs suitable for outdoor daylight applications also.
(Not for use against direct sunlight) . Clock should be used under a shade protected from direct rains .

Accessories Included : External wired remote control with 3 meter long connector cable .
This handy push button control has only 3 buttons for START , STOP & RESET .

Manufactured by:

COSY COMMUNICATIONS , 1, Indraprastha Enclave , Sewla, Majra, Dehradun - 248 171 (INDIA)

Tele:91-135-2640816 E-Mail: cosycom@gmail.com , Web : www.cosycom.com